

BANHAM

SECURITY

KEYFOB PROGRAMMING FOR APP PANEL

1. With the keypad displaying: Press the **D button** then enter the Master Manager code.
2. If the correct code is entered the keypad will display:
3. Press the **NO button** on the keypad and the screen will display:
4. Press the **NO button** on the keypad and the screen will display:
5. Press the **NO button** on the keypad and the screen will display either:
6. Press the **YES button** and the screen will display:
7. Press the **YES button** on the keypad and the screen will display: This is the next available user position meaning all the previous ones have been allocated.
8. Press the **YES button** on the keypad and the screen display:
9. Present the new key tag to the keypad (where the BANHAM GROUP logo is), You will hear a beep and the display will show six (6) asterisk / stars within the brackets.
10. Press the **YES button** on the keypad and the screen will display:
11. Press the **YES button** on the keypad and the screen will display: Using the ABCD buttons, choose the areas you wish to be controlled by that key tag. **Default is User Areas (ABCD)**.
12. Press the **YES button** on the keypad and the screen will display: Default is Unset / Set (0) however if you wish to change it press **D** to toggle through the options.
13. Press the **YES button** on the keypad and the screen will display: **Flexi set Yes** gives you the opportunity to choose the areas you require to set with the key tag, i.e. A = Full set. B = Night set. **Flexi set NO** will simply set the areas assigned without offering you the opportunity to choose. To toggle between **YES** and **NO** press the **D button**.
14. Press **YES button** on the keypad and the screen will display: **(If no user name is required press the YES button)**. Press the numbers on the keypad to select the first letter of the user name, (predictive text may choose a name) providing the first letter is correct press the **D button** to move the cursor position and repeat. Use the **B button** to move back and the **C button** to clear. Press the **YES button** on the keypad.
15. The display will show: If additional key tags are required to be added repeat from step 7. **OR** If no further key tags are required press the **NO button FOUR (4)** times and the screen will display either:
16. Press the **A button** and after a few seconds the screen will display:

BANHAM SECURITY
TIME: 09:15

SET DATE & TIME ?

OPERATE USER
OUTPUTS ?

OMIT INPUTS ?

EDIT USERS ? **OR**
CHANGE CODES ?

Add New User ?

Empty [04]

Enter User Code
[]

User Type
User [0]

User Areas
[ABCS]

User Set Options
Unset/Set [0]

Flexi Set
No [0]

User Name
-

Empty [05]

EDIT USERS ? **OR**
CHANGE CODES ?

BANHAM SECURITY
TIME: 09:15

Please test the new key tags and record the user name and number on the back of this sheet and retain in a secure place for future reference.

KEYFOB PROGRAMMING FOR APP PANEL

USER NUMBER	USER TYPE	AREAS	SET/UNSET	FLEXI SET	USER NAME
EXAMPLE	USER	ABCD	(0)	YES (1)	JOHN
EXAMPLE	USER	A	(0)	NO (0)	CLEANER
01					
02					
03					
04					
05					
06					
07					
08					
09					
10					
11					
12					
13					
14					
15					
16					
17					
18					
19					
20					
21					
22					
23					
24					
25					
26					
27					
28					